



From	To	Conductor	Color
E1.1	S1	W1.Brown	Brown
E1.2	S2	W2.Pink	Pink
E1.3	Inj1_1.1	W3.Dark Green	Dark Green
E1.4	Inj1_2.1	W4.Dark Green	Dark Green
E1.5	Inj2_1.1	W6.Blue	Blue
E1.6	Inj2_2.1	W7.Blue	Blue
E1.7	Head_Cylinder	W9.Green-Yellow	Green-Yellow
E1.8	S3	W10.Red	Red
E1.9	Pick_up.2	W11.Gray	Gray
E1.10	TMAP.2	W12.White	White
E1.11	CLT.2	W13.Orange	Orange
E1.12	TPS.2	W14.Green	Green
E1.13	TMAP.4	W15.Yellow	Yellow

From	To	Conductor	Color
S1	CLT.1	W23.Brown	Brown
S1	E1.1	W1.Brown	Brown
S1	Pick_up.1	W16.Brown	Brown
S1	TMAP.1	W18.Brown	Brown
S1	TPS.1	W24.Brown	Brown
S2	E1.2	W2.Pink	Pink
S2	Pick_up.3	W17.Pink	Pink
S2	TMAP.3	W19.Pink	Pink
S2	TPS.3	W5.Pink	Pink
S3	E1.8	W10.Red	Red
S3	Inj1_1.2	W8.Red	Red
S3	Inj1_2.2	W20.Red	Red
S3	Inj2_1.2	W21.Red	Red
S3	Inj2_2.2	W22.Red	Red

From	To	Conductor	Color
Head_Cylinder	E1.7	W9.Green-Yellow	Green-Yellow

From	To	Conductor	Color
Pick_up.1	S1	W16.Brown	Brown
Pick_up.2	E1.9	W11.Gray	Gray
Pick_up.3	S2	W17.Pink	Pink

From	To	Conductor	Color
TMAP.1	S1	W18.Brown	Brown
TMAP.2	E1.10	W12.White	White
TMAP.3	S2	W19.Pink	Pink
TMAP.4	E1.13	W15.Yellow	Yellow

From	To	Conductor	Color
Inj1_1.1	E1.3	W3.Dark Green	Dark Green
Inj1_1.2	S3	W8.Red	Red

From	To	Conductor	Color
Inj1_2.1	E1.4	W4.Dark Green	Dark Green
Inj1_2.2	S3	W20.Red	Red

From	To	Conductor	Color
Inj2_1.1	E1.5	W6.Blue	Blue
Inj2_1.2	S3	W21.Red	Red

From	To	Conductor	Color
Inj2_2.1	E1.6	W7.Blue	Blue
Inj2_2.2	S3	W22.Red	Red

From	To	Conductor	Color
TPS.1	S1	W24.Brown	Brown
TPS.2	E1.12	W14.Green	Green
TPS.3	S2	W5.Pink	Pink

From	To	Conductor	Color
CLT.1	S1	W23.Brown	Brown
CLT.2	E1.11	W13.Orange	Orange

Title Loom - PFI - Engine - Assembly		Part Number 70-0327-R00A-Wiring Diagram		Revision R00A	
Description Loom - PFI - Engine - Assembly		Revision R00A		QA	
Drawn By	----	Date	----	Eng Approved	
Mfg Approved		----		QA	
Name		Date		This document contains confidential and proprietary information that cannot be reproduced or divulged, in whole or in part, without written authorization.	



<b>Title:</b>	Loom - PFI - Engine - Assembly - Wiring Table
<b>Part Number:</b>	70-0327-R00A-Wiring Diagram - A
<b>Description:</b>	Loom - PFI - Engine - Assembly



From	To	Conductor	Notes
CLT.1	S1	W23.Brown	Sig - GND
E1.1	S1	W1.Brown	Sig - GND
E1.2	S2	W2.Pink	+5V
E1.3	Inj1_1.1	W3.Dark Green	INJ 1 - 1.1
E1.4	Inj1_2.1	W4.Dark Green	INJ 3 - 1.2
E1.5	Inj2_1.1	W6.Blue	INJ 2 - 2.1
E1.6	Inj2_2.1	W7.Blue	INJ 4 - 2.2
E1.7	Head_Cylinder	W9.Green-Yellow	Head GND
E1.8	S3	W10.Red	INJ +12v
E1.9	Pick_up.2	W11.Gray	Signal - Crank Pos
E1.10	TMAP.2	W12.White	Signal - MAP
E1.11	CLT.2	W13.Orange	Signal - Engine Temp
E1.12	TPS.2	W14.Green	Sig - TPS
E1.13	TMAP.4	W15.Yellow	Sig - Air Temp
Inj1_1.2	S3	W8.Red	INJ +12v
Inj1_2.2	S3	W20.Red	INJ - 12v
Inj2_1.2	S3	W21.Red	INJ - 12v
Inj2_2.2	S3	W22.Red	INJ - 12v
Pick_up.1	S1	W16.Brown	Sig - GND
Pick_up.3	S2	W17.Pink	Sig - 5V
TMAP.1	S1	W18.Brown	Sig - GND
TMAP.3	S2	W19.Pink	Sig - 5V
TPS.1	S1	W24.Brown	Sig - GND
TPS.3	S2	W5.Pink	+5V